

**Schematic Key for Multilayer and HDI-Technology Build-Ups**

a	b	c	d	e	f	g + h + i
---	---	---	---	---	---	-----------

**06 319 FR4 35 L71.35 P10\_18 S1**

columns and equal kind of positions are separated by "\_". Equal prefixes in one column are reduced to one.

**06\_319\_FR4\_35\_L71.35\_p10\_18\_s1**

Layers	in $\mu$	Material	Build-Up	Assembly
<b>Layer-1</b>	35 $\mu$	Copper	<p>(100 <math>\mu</math> PrePreg-Type: 2125)</p>	
	100 $\mu$	Prepreg		
	100 $\mu$	Prepreg		
	100 $\mu$	Prepreg		
<b>Layer-2</b>	35 $\mu$	Copper		
	710 $\mu$	L-FR4		
	35 $\mu$	Copper		
<b>Layer-3</b>	35 $\mu$	Copper	<p>(180 <math>\mu</math> PrePreg-Type: 7628)</p>	
	180 $\mu$	Prepreg		
	180 $\mu$	Prepreg		
	180 $\mu$	Prepreg		
<b>Layer-4</b>	35 $\mu$	Copper		
	710 $\mu$	L-FR4		
	35 $\mu$	Copper		
<b>Layer-5</b>	35 $\mu$	Copper		
	180 $\mu$	Prepreg		
	180 $\mu$	Prepreg		
	180 $\mu$	Prepreg		
<b>Layer-99</b>	35 $\mu$	Copper		

© Copyright by Printed Circuit Boards GmbH